Distributed by:

JAMECO® ELECTRONICS

www.Jameco.com ✦ 1-800-831-4242

The content and copyrights of the attached material are the property of its owner.

Digital Multimeter

Digital Multimeter

FEATURES :

*** 8 Functions AC/DC Voltage, AC/DC Current, Resistance Capacitance, Diode Test and Audible Continuity Beeper**
*** High Voltage 1000V and 20A Current Range**
*** 0.5% Basic DCV Accuracy**
*** LCD Display**

GDM-8034 (3 1/2 Digits)

SPECIFICATIONS		
DC VOLTAGE	**Range** **Accuracy** **Input Impedance**	200mV, 2V, 20V, 200V, 1000V 5ranges. ±(0.5% rdg + 1 digit) 10MW
AC VOLTAGE	**Range** **Accuracy** **Input Impedance**	200mV, 2V, 20V, 200V, 750V 5ranges. 40Hz ~ 500Hz± (1% rdg + 4 digits) 10MW
DC CURRENT	**Range** **Accuracy**	200μA, 2mA, 20mA, 200mA, 2A, 20A 6 ranges 200μA ~ 200mA±(0.5% rdg + 1 digit) 2A ~ 20A±(1% rdg + 3 digits)
AC CURRENT	**Range** **Accuracy**	200μA, 2mA,20mA,200mA, 2A,20A 6 ranges 40Hz ~ 500Hz on all ranges, 200μA ~ 200mA±(1% rdg + 4 digits) 2A ~ 20A±(1.5% rdg + 2 digits)
RESISTANCE	**Range** **Accuracy**	200W, 2k, 20k, 200kW, 2MW, 20MW6 ranges. 200W ~ 2MW±(0.75% rdg + 1 digit), 20MW±(1.5% rdg + 5 digits)
CAPACITANCE	**Range** **Accuracy** **Test Freq.**	2nF, 20nF, 200nF, 2μF, 20 μF 5 ranges ±(2% rdg + 4 digits) 300Hz±5%
DIODE TEST	**Test Current** **Open Voltage**	Max. 2.5mA Max. 3.2V
CONTINUITY BEEPER	**Description** **Test Current** **Open Voltage**	Buzzer sounds if conductance less than 30W Max. 2.5 mA Max. 3.2V
DISPLAY		0.5" LCD display
POWER SOURCE		AC 110V/220V± 15%, 50/60Hz
ACCESSORIES		Power cord x 1, Instruction manual x 1, Test lead GTL-107A x 1
DIMENSIONS & WEIGHT		245(W) x 95(H) x 280(D) mm, Approx. 2kg

ISO-9001 & ISO-14001